

## 260-2696 Digital Event Counter

The **Model 260-2596 Digital Event Counter** is useful for counting tips at sites where monitoring equipment has no local display capability. The counter has a reset button on the display face and the liquid crystal display is visible even in bright sunlight.

The 260-2596 is a general purpose, miniature digital event counter that operates from switch contact or NPN open collector inputs. This unit provides years of silent operation without mechanical wear and is self-powered with a 2-wire connection that eliminates power wiring.

### Specifications

Display: 6-digit LCD, 0.2" high  
Power: 3 volts  
Battery: Lithium  
Count input: Switch contact or solid-state transistor switch.  
Count speed: 100 counts/sec.  
Operating temperature: -30 °C to +75°C  
Weight: 3 oz. without batteries

### Ordering Information

260-2596      Digital Event Counter



260-2596 Digital Event Counter